

REMARKS

The above-noted amendments of claims 1-23 as well as the submission of a new Abstract and revisions to the Specification, are respectfully submitted prior to the initiation of prosecution of this application in the U.S. Patent and Trademark Office.

The above-noted amended claims are respectfully submitted in order to more clearly and appropriately claim the subject matter which applicant considers to constitute his inventive contribution. None of these claim amendments are for any purpose related to patentability. No new matter is included in these amendments. In addition, the revisions to the Abstract and Specification are submitted in order to clarify and correct the Abstract and Specification and to conform them to all of the requirements of U.S. practice. No new matter is included in these amendments.

In view of the above, it is respectfully requested that these amendments now be entered, and that prosecution on the merits of this application now be initiated. If, however, for any reason the Examiner does not believe such action can be taken, it is respectfully requested that he telephone applicant's attorney at (908) 654-5000 in order to overcome any objections which he may have.



MARKED-UP COPY OF AMENDED SPECIFICATION PARAGRAPHS:

CONTROL METHOD AND COMMUNICATION DEVICE

BACKGROUND OF THE INVENTION

[0001] The present invention relates to a control method applied to data transmission between devices connected through a network of IEEE (The Institute of Electrical and Electronics Engineers) 1394 bus lines or the like and a communication device to which the control method is applied.

~~Description of the Prior Art~~

[0002] AV devices ~~which can transmit~~ information to each other through a network using an IEEE 1394 serial data bus. ~~are developed.~~ When data transmission is performed through the bus, a synchronous communication mode is used when audio data or the like is transmitted ~~enin~~ real time and an asynchronous communication mode is used when a static image, text data, a control command, or the like is reliably transmitted. ~~are prepared,~~ Bands dedicated to the respective modes are used in transmission. In the IEEE 1394 scheme, the synchronous communication mode is called an isochronous communication mode, and the asynchronous communication mode is called an asynchronous communication mode.

[0003] In communication in the isochronous communication mode, a device set as an IRM (Isochronous Resource Manager) in a network manages a channel and a band. ~~and a~~ A device for executing communication in isochronous communication mode performs the process of obtaining a channel and a band ~~to~~ for the IRM. The channel ~~mentioned here~~ is a path for flowing isochronous data between a transmission side and a reception side. ~~and~~ the band ~~mentioned here~~ is in proportion to the size of a packet transmitted on one channel, and is in an ~~band~~ amount ~~isochronous communication which that is in~~ inversely proportional to a transmission rate.

[0004] By using the obtained channel and band, isochronous data is transmitted between the connected devices. ~~which connection is set. As settings of the connection,~~ Devices are connected using known connection technology, including a point-to-point connection (called a PtoP connection) for connecting an output plug of one device and an input plug of another device, and a broadcast connection for performing transmission by using a channel for broadcast ~~are known.~~

[0005] In communication in the asynchronous communication mode, an input plug and an output plug which are different from those in the isochronous communication mode are ~~set~~used, and communication is executed by a control process which is different from that in the isochronous communication mode.

[0006] A communication circuit included in a device connected to the IEEE 1394 bus line, as described above, has ~~two~~two communication modes having different communication forms. Since the communication circuit is designed such that communication in the isochronous communication mode and communication in the asynchronous communication mode can be executed, the communication circuit has the disadvantage of having a circuit configuration having that has a relatively large scale and a relatively high power consumption, ~~disadvantageously.~~

[0007] ~~Basically,~~ In a device connected to the conventional IEEE 1394 bus line, the bus line has only two states. ~~, i.e.,~~ aIn one state in which communication through the bus line can be performed and aIn the other state in which communication through the bus line cannot be performed at all because the power supply of the device is in an OFF state or a standby state ~~can be selected.~~ Therefore, when the power supply of the device is turned on to set the device in a state in which communication can be performed, a communication circuit connected to the bus line is always ~~operates~~operable to consume power for the communication process.

[0008] The communication process in the device connected to the IEEE 1394 bus line has been described above. However, a similar problem is posed in communication devices for various communication methods which can perform communication in a synchronous communication mode and ~~communication~~ in an asynchronous communication simultaneously.

SUMMARY OF THE INVENTION

[0009] It is an object of the present invention to reduce a the power consumption required for communication in a communication device connected to a network of this type.

[0010] In a control device according to the first aspect of the present invention, a first power supply ~~of a part~~ for executing a communication process in a synchronous communication mode is controlled independently of a second power supply ~~of a part~~ for executing a communication process in an asynchronous communication mode.

[0011] According to the first aspect of the present invention, the first power supply ~~of only the part~~ for executing the communication process in the synchronous communication mode is independently controlled. For example, when synchronous communication need not be performed, the first power supply ~~of the part~~ can be turned off.

[0012] In a control method according to the second aspect of the present invention, ~~a~~ the second power supply ~~of a part~~ for executing a communication process in an asynchronous communication mode is controlled independently of a the first power supply ~~of a part~~ for executing a communication process in a synchronous communication mode.

[0013] According to the second aspect of the present invention, the second power supply ~~of only the part~~ for executing the communication process in the asynchronous communication mode is independently controlled. For example, when asynchronous

communication need not be performed, the second power supply of ~~the part~~ can be turned off.

[0014] A communication device according to the third aspect of the present invention includes a first communication process unit for performing a communication process in a synchronous communication mode, a second communication process unit for performing a communication process in an asynchronous communication mode, an input/output unit for performing a process between the first and second communication process units and a network, and a control unit which controls the synchronous communication and the asynchronous communication and can independently control ~~only~~ the first power supply of the first communication process unit.

[0015] According to the third aspect of the present invention, ~~only~~ the first power supply of the first communication process unit for executing the communication process in the synchronous communication mode can be independently controlled by ~~the control of~~ the control unit. For example, if the synchronous communication need not be performed, the power supply of ~~only~~ the first communication process unit can be turned off.

[0016] ~~In a~~ communication device according to the fourth aspect of the present invention includes a first communication process unit for performing a communication process in a synchronous communication mode, a second communication process unit for performing a communication process in an asynchronous communication mode, an input/output unit for performing a process between the first and second communication process units and a network, and a control unit which controls the synchronous communication and the asynchronous communication and can independently control ~~only~~ the second power supply of the second communication process unit.

[0017] According to the fourth aspect of the present invention, ~~only~~ the second power supply of the second

communication process unit for executing the communication process in the asynchronous communication mode can be independently controlled by the control of the control unit. For example, if the asynchronous communication need not be performed, the power supply of ~~only~~ the second communication process unit can be turned off.

BRIEF DESCRIPTION OF THE DRAWINGS

[0018] FIG. 1 is a block diagram showing an example of the configuration of an entire system according to an embodiment of the present invention;

[0019] FIG. 2 is a block diagram showing an example of the internal configuration of an IRD and a disk recording/reproducing device according to an embodiment of the present invention;

[0020] FIG. 3 is a block diagram showing an example of the configuration of a communication process unit according to an embodiment of the present invention;

[0021] FIG. 4 is a diagram ~~for~~ explaining an example of the cycle structure of data transmission on an IEEE 1394 bus;

[0022] FIG. 5 is a diagram ~~for~~ explaining an example of the structure of an address space of a CRS architecture;

[0023] FIG. 6 is a diagram ~~for~~ explaining examples of the position, name, and operation of a main CRS;

[0024] FIG. 7 is a diagram ~~for~~ explaining an example of a general ROM format;

[0025] FIG. 8 is a diagram ~~for~~ explaining examples of a bus info block, a root directory, and a unit directory;

[0026] FIG. 9 is a diagram ~~for~~ explaining an example of the configuration of a PCR;

[0027] FIGS. 10A to 10D are diagrams ~~for~~ explaining examples of the configurations of oMPR, an oPCR, and iPCR;

[0028] FIG. 11 is a diagram ~~for~~ explaining an example of the relationship among a plug, a plug control register, and a transmission channel;

[0029] FIG. 12 is a diagram ~~for~~ explaining an example of the data structure obtained by the hierarchical structure of a descriptor;

[0030] FIG. 13 is a diagram ~~for~~ explaining an example of the data format of the descriptor;

[0031] FIG. 14 is a diagram ~~for~~ explaining an example of a generation ID in FIG. 13;

[0032] FIG. 15 is a diagram ~~for~~ explaining an example of a list ID in FIG. 13;

[0033] FIG. 16 is a diagram ~~for~~ explaining an example of the stack model of an AV/C command;

[0034] FIG. 17 is a diagram ~~for~~ explaining the relationship between a command and a response of an FCP;

[0035] FIG. 18 is a diagram ~~for~~ explaining the relationship between the command and the response in FIG. 17 in detail;

[0036] FIG. 19 is a diagram ~~for~~ explaining an example of the data structure of an AV/C command;

[0037] FIGS. 20A to 20C are diagrams ~~for~~ explaining concrete examples of AV/C commands;

[0038] FIGS. 21A and 21B are diagrams ~~for~~ explaining concrete examples of a command and a response of an AV/C command;

[0039] FIG. 22 is a diagram ~~for~~ explaining an example of the relationship between a state of a plug and a connection;

[0040] FIG. 23 is a flow chart showing an example of a power supply control process of an isochronous block; and

[0041] FIG. 24 is a flow chart showing another example of the power supply control process of an isochronous block.

DETAILED DESCRIPTION OF THE PREFERRED EMBODIMENTS

[0042] An embodiment of the present invention will be described below with reference to the accompanying drawings.

[0043] An example of the configuration of a network system to which the present invention is applied will be described below with reference to FIG. 1. In this network system, a plurality of

devices are connected through a cable 26 constituting an IEEE 1394 serial data bus. In this case, as shown in FIG. 1, an IRD (Integrated Receiver Decoder) 10 having a terminal for connecting an IEEE 1394 bus and a disk recording/reproducing device 50 are connected to the cable 26. The cable 26 corresponds to the IEEE 1394 bus line.

[0044] The IRD 10 is a digital satellite broadcast receiver, and is designed to ~~a receiving process of a signal channel input received~~ through a connected antenna 30 and also to perform a demodulation process or the like of a broadcast signal of the received channel. ~~In this case, as the channel which can be received,~~ In addition to a television broadcasting channel constituted by comprising a video signal and an audio signal, the received channel also can contain a radio broadcasting channel constituted by comprising an audio signal or a data broadcasting channel exists.

[0045] A television monitor 40 is connected to the IRD 10 through an analog cable. A program received by the IRD 10 can be viewed and heard with the monitor 40. The television monitor 40 may be connected to the cable 26 so that video data or the like may be transmitted to the television monitor 40 through the cable 26.

[0046] The disk recording/reproducing device 50 is a device which uses a photomagnetic disk called a mini disk (MD) or an optical disk as a recording medium to record and reproduce an audio signal or the like.

[0047] In FIG. 1, ~~at the network configuration is a most simple configuration in which shows~~ only two devices are connected to the cable 26 serving as a bus line. However, ~~another devices is can be connected to the cable 26, so that to obtain a larger network configuration can also be obtained.~~

[0048] FIG. 2 is a diagram showing the details of a configuration which receives a broadcast signal of a digital

satellite broadcast system and records the broadcast signal. A broadcast radio wave from a satellite (not shown) is received by the antenna 30 and transmitted to a tuner 11 serving as a program selection means arranged in the IRD 10 serving as a program receiving device. The IRD 10 is designed such that respective circuits operate on the basis of the control of a CPU 20. A reception signal S30 from a transponder selected by the tuner 11 is transmitted to a front-end unit 12.

[0049] The front-end unit 12 demodulates the reception signal S30 and performs an error correction process to reception data obtained as a result of the demodulation. Thereafter, the reception data is transmitted to a descramble circuit 13 as a reception data stream D31.

[0050] The descramble circuit 13, on the basis of cryptograph key information of a contract channel stored in an IC card (not shown) inserted into the body of the IRD 10, extracts multiplexing data D32 of the contract channel from the reception data stream D31 to transmit the multiplexing data D32 to a demultiplexer 14.

[0051] The demultiplexer 14 rearranges the multiplexing data D32 in units of channels, extracts only a channel designated by a user, transmits a video stream D33 ~~constituted by~~ comprising the packet of a video portion to an MPEG video decoder 15, and transmits an overlap stream D34A ~~constituted by~~ comprising the packet of an audio portion to an MPEG audio decoder 16.

[0052] The MPEG video decoder 15 decodes the video stream D33 to recover video data D35 obtained before compression coding, and transmits the recovered video data D35 to an NTSC encoder 17. The NTSC encoder 17 converts the video data D35 into a luminance signal and a color difference signal of the NTSC system, and transmits the luminance signal and the color difference signal to a digital_-analog conversion circuit 18 as NTSC data D36. The digital_-analog conversion circuit 18 converts the NTSC data D36

into an analog signal S37 and outputs the analog signal S37 to the monitor 40.

[0053] The MPEG audio decoder 16 decodes the overlap stream D34A to recover a PCM (Pulse Code Modulation) audio data D38 obtained before compression coding, and transmits the PCM audio data D38 to a digital-analog conversion circuit 19. The PCM audio data D38 is supplied to an interface 24, and can be transmitted to athe bus line 26. In addition, the PCM audio data D38 can be directly transmitted to athe disk recording/reproducing device 50 through a cable 27 which is not a bus line.

[0054] The digital-analog conversion circuit 19 converts the PCM audio data D38 into an analog signal to generate an LCh audio signal S39A and an RCh audio signal S39B, outputs the LCh audio signal S39A and the RCh audio signal S39B as a speech through a loudspeaker (not shown) of the monitor 40, and transmits the LCh audio signal S39A and the RCh audio signal S39B to an analog-digital conversion circuit 58 of the disk recording/reproducing device 50.

[0055] When a music channel of contract channels is designed, the demultiplexer 14 transmits the audio stream D34A of the multiplexing data D32 to the MPEG audio decoder 16 and outputs speech-added information stream D34B serving as added information ~~constituted by comprising~~ the packets of speech-added information to the CPU 20 through the IEEE 1394 interface 24.

[0056] The CPU 20 generates title data D40 from the packets of the speech-added information stream D34B expressed by characters, numbers, and the like on the basis of ID (Identification) numbers added to the packets.

[0057] At this time, the CPU 20, serving as a recording control means, generates recording control data D41 serving as a control signal for controlling a recording operation such as a recording start operation or a recording stop operation on the

basis of a recording instruction input by a user through an operation button (not shown) on an operation panel 23, and returns the recording control data D41 and the title data D40 as control data D42 to the IEEE 1394 interface 2624.

[0058] The IEEE 1394 interface 2624 transmits the control data D42 supplied from the CPU 20 from the IEEE 1394 cable 26 serving as a data transmission/reception means to a CPU 52 through an IEEE 1394 interface 51 of the disk recording/reproducing device 50 serving as a data recording reproducing means, and transmits the PCM audio data D38 from the IEEE 1394 cable 26 to an ATRAC encoder 53 through the IEEE 1394 interface 51.

[0059] The ATRAC encoder 53 is highly efficiently and codes the PCM audio data D38 by the ATRAC system on the basis of the control of the CPU 52, and transmits the coded data to a recording/reproducing system 54 as PCM audio data D43.

[0060] The CPU 52 of the disk recording/reproducing device 50 is designed to control recording operations of a recording/reproducing system 54 and an optical pickup 55 on the basis of the recording control data D41 of the control data D42. Adding an error correction code and a predetermined modulation process to the PCM audio data D43 are performed by the recording/reproducing system 54. Thereafter, the PCM audio data D43 is recorded as recording data D44 in a designated region of a photomagnetic disk 56 serving as a recording medium through the optical pickup 55.

[0061] The CPU 52 of the disk recording/reproducing device 50 controls recording operations of the recording/reproducing system 54 and the optical pickup 55 on the basis of the recording control data D41, so that, of the title data D40, data expressed by half-size katakana and alphanumerical characters is recorded as kana alphanumerical code title data D40A in a predetermined area of the photomagnetic disk 56, and records data expressed by

full-size kanji and hiragana characters as kanji code title data D40B in a predetermined area.

[0062] In this manner, the IRD 10 controls the recording operation of the disk recording/reproducing device 50 by the CPU 20 ~~to make it possible so~~ that the PCM audio data D38 can be recorded in a predetermined region of the photomagnetic disk 56 and to record the title data D40 corresponding to the PCM audio data D38 to be recorded in a predetermined area (TOC area) of the photomagnetic disk 56.

[0063] In reproduction, the disk recording/reproducing device 50 transmits reproduced data D45 reproduced by the optical pickup 55 to the recording/reproducing system 54. The recording/reproducing system 54 performs an error correction process and a predetermined demodulation process to the reproduced data D45 and transmits the reproduced data D45 to an ATRAC decoder 57 as reproduced data D46.

[0064] The ATRAC decoder 57 decodes the reproduced data D46 by the ATRAC system. The ATRAC decoder 57 externally outputs the decoded data D46 as digital reproduced data D47 through an optical digital cable 60 or converts the decoded data D46 into an analog LCh audio signal S48 and an analog RCh audio signal S49 to output the LCh audio signal S48 and the RCh audio signal S49 as speech from loudspeakers ~~61L62L~~ and ~~61R62R~~ connected to an amplification device 61.

[0065] The disk recording/reproducing device 50 reads title data D50 corresponding to the reproduced data D45, which is being reproduced, from the TOC 1 area or the TOC 4 area of the photomagnetic disk 56 by the optical pickup 55 and transmits the title data D50 to the recording/reproducing system 54. The recording/reproducing system 54 performs an error correction process and a predetermined demodulation process to the title data D50 and then transmits the processed title data D50 as title data D51 to the CPU 52.

[0066] The CPU 52 stores the title data D51 in a RAM 52A and transmits the title data D51 to a RAM 21 through the IEEE 1394 interface 51, the IEEE 1394 cable 26, the IEEE 1394 interface 24, and the CPU 20 to store the title data D51 in the RAM 21 serving as a storage means.

[0067] In this state, when instruction information for displaying image data corresponding to the title data D51 on the monitor 40 is input through an operation panel 46, the CPU 20 serving as a display control means reads title data D52 from the RAM 21 and transmits the title data D52 to the MPEG video decoder 15. The MPEG video decoder 15 performs a predetermined graphics process to the title data D52, and transmits the resultant image data to the monitor 40 through the NTSC encoder 17 and the digital-analog conversion circuit to display a GUI (Graphic User Interface) screen on the monitor 40 serving as the display means.

[0068] In reproduction from the disk, the reproduced audio data or the like may be transmitted from the IEEE 1394 interface 51 to another device through the cable 26.

[0069] ~~The configuration for performing e~~Communication of the above-described devices (in this case, the IRD 10 and the disk recording/reproducing device 50) ~~constituted as described above and connected to the cable 26,~~ serving as an IEEE 1394 bus line, through the bus line of the devices will be described below with reference to FIG. 3.

[0070] In FIG. 3, a communication process block 100 is a processing block for performing communication with another device through the cable 26. This communication process block 100 corresponds to the IEEE 1394 interface 24 when the IRD 10 is used, and corresponds to the IEEE 1394 interface 51 when the disk recording/reproducing device 50 is used. ~~In addition, a~~ communication process in the communication process block 100 is executed by ~~the control of a~~ control unit 120. This control unit 120 corresponds to the CPU 20 when the IRD 10 is used, and

corresponds to the CPU 52 when the disk recording/reproducing device 50 is used. In addition, a process for stream data transmitted by the communication process block 100 or a process for received stream data are executed by a signal processing unit 130. This signal processing unit 130 corresponds to a block for receiving broadcast data when the IRD 10 is used, and corresponds to a block for recording stream data on a disk and reproducing the stream data when the disk recording/reproducing device 50 is used.

[0071] In FIG. 3, a power supply circuit 140 for supplying a power to these blocks is shown. Control unit 120 controls ~~Tthe~~ supply state of the power supply from the power supply circuit 140 ~~is controlled by the control unit 120~~. In particular, a power supply to an isochronous block 110 (to be described later) can be controlled independently of a power supply to another block. The details of the power supply process will be described later. In addition, an operation key pad 150 for setting the operations states of the devices is connected to the control unit 120. This operation key pad 150 ~~is constituted by~~ comprises, for example ~~e.g.~~, the operation panel 23 in the IRD 10 shown in FIG. 2.

[0072] The configuration of the communication process block 100 for performing communication with an IEEE 1394 bus line will be described below. A physical layer (PHY layer) 101 is ~~Aan~~ input/output unit of ~~this communication process block 100 and is~~ directly connected to the cable 26 ~~is called as a physical layer (PHY layer) 101~~. ~~In this p~~Physical layer 101 performs, an input process from the bus line and an output process to the bus line ~~are performed~~.

[0073] ~~To the physical layer 101,~~ a reception unit 103 and a transmission unit 104 are connected to the physical layer 101 through a physical layer interface unit 102. ~~Here,~~ for ~~t~~Transmission in the IEEE 1394 bus line, 26 can be in isochronous

~~and asynchronous communication modes. In communication in an isochronous communication mode, which is a mode in which stream data is synchronously communicated, and communication in an In asynchronous communication mode, which is a mode in which control data is asynchronously communicated can be performed.~~ In the reception unit 103 and the transmission unit 104, the processes ~~inof~~ both ~~the~~ communication modes can be performed. More specifically, ~~in the reception unit 103, of data transmitted through the bus line in isochronous communication mode, data the destination of which is set as the device is received, and data that is destined for receipt in the reception unit 103 is received in the isochronous communication mode, and then is supplied to an isochronous data buffer 112 in the isochronous block 110. Data received in the asynchronous communication mode is supplied to an asynchronous data buffer 105. The transmission unit 104 performs a transmitting processes to the transmitted data supplied from the isochronous data buffer 112 in the isochronous communication mode in the isochronous block 110, in the isochronous communication mode, and performs a transmission processes to the transmitted data supplied from the asynchronous data buffer 105 in the asynchronous communication mode.~~

[0074] The isochronous block 110 ~~is constituted by~~ comprises an isochronous signal processing unit 111 and an isochronous data buffer 112. Isochronous data in units of received packets is supplied to the isochronous signal processing unit 111 through the buffer 112, and continuous stream data is obtained on the basis of a time stamp added to the data. The obtained stream data is supplied to the signal processing unit 130. ~~When the stream data transmitted from the signal processing unit 130 is supplied, t~~The stream data is then divided by the isochronous signal processing unit 111 into isochronous data in units of packets, and time stamps are added to the data of the respective packets. The packets of isochronous data ~~divided in units of~~

~~packets~~ are transmitted to the transmission unit 104 through the buffer 112. ~~At a timing at which data is input to or output from the isochronous data buffer 112 is controlled by t~~The isochronous signal processing unit 111, the reception unit 103, and the transmission unit 104 control the timing of the data input to or output from the isochronous data buffer 112.

[0075] In this embodiment, ~~T~~the isochronous signal processing unit 111 and the buffer 112 in the isochronous block 110 ~~in this embodiment~~ are designed such that the power supplies of the isochronous signal processing unit 111 and the buffer 112 are controlled independently of the other circuits in the communication process block 100. More specifically, when power is supplied to the other circuits in the communication process block 100, the power supply to the isochronous block 110 can be stopped.

[0076] An asynchronous signal processing unit 106 is connected to the asynchronous data buffer 105. ~~r~~ dData (asynchronous packet) received in the asynchronous communication mode is ~~determined~~ processed by the asynchronous signal processing unit 106, and is supplied to the control unit 120 if necessary. Data (asynchronous packet) transmitted from the asynchronous signal processing unit 106 is supplied to the transmission unit 104 through the buffer 105. A register 107 for managing communication is connected to the asynchronous signal processing unit 106. ~~By~~ From the received data, data is written in the register 107, and a response to the data read from the register 107 is performed. The configuration of the register 107 will be explained in the description of a communication process configuration of the IEEE 1394 system.

[0077] However, by using a partial storage area, a plug control register is prepared for ~~imaginarily~~ virtually setting plugs in the respective communication modes ~~is prepared~~. When isochronous communication is performed by the isochronous block

110, reading and writing of the plug control register are performed in the asynchronous communication mode to extend connection and to perform communication.

[0078] Control unit 120 determines ~~the value of the plug control register in the register 107 can be determined by the control unit 120.~~

[0079] A communication state in an IEEE 1394 bus line and a process configuration required for the communication will be described below. FIG. 4 is a diagram showing the cycle structure of data transmission of devices connected by the IEEE 1394 bus line. In the IEEE 1394 bus line, data is divided into packets, and the packets are time-divisionally transmitted with reference to a cycle having a length of 125 μ S. This cycle is started made by a cycle start signal supplied from a node (one of the devices connected to the bus) having a cycle master function. An isochronous packet secures a band (although the band is a time unit) required for transmission from the starts of all the cycles. ~~For this reason~~ Thus, in isochronous transmission, transmission of data within a predetermined period of time is assured. However, if a transmission error is generated, a protecting device is ~~not arranged~~ present, and data is lost.

[0080] ~~In~~ During a period of time ~~which that~~ is not used for isochronous transmission of each cycle, a node ~~which~~ secures a bus as a result of arbitration and transmits an asynchronous packet in the asynchronous transmission. ~~However, in the asynchronous transmission asynchronous packet, by using acknowledge and retry, reliable transmission is assured,~~ By using acknowledge and retry commands, reliable transmission of the asynchronous packets is assured, but ~~at~~ the transmission timing is not constant.

[0081] In order to cause a predetermined node to perform isochronous transmission, the node must correspond to an isochronous function. At least one of the nodes corresponding to

the isochronous function must have a cycle master function. In addition, at least one of the nodes connected to the IEEE 1394 serial bus must have the function of isochronous resource manager.

[0082] The IEEE 1394 conforms to a CSR (Control & Status Register) architecture having a 64-bit address space regulated by ISO/IEC 13213. FIG. 5 is a diagram ~~for~~ explaining the structure of the address space of the CSR architecture. This data is registered and set in the register 107 shown in FIG. 3 ~~and set~~. The upper 16 bits correspond to a node ID representing a node on each IEEE 1394 bus line, and the remaining 48 bits are used to designate an address space given to each node. The upper 16 bits are divided into 10 bits ~~ef~~ for a bus ID and 6 bits ~~ef~~ for a physical ID (which strictly means a node ID). Since ~~at~~ the value at which ~~all~~ each of the bits are ~~is~~ 1 each is used for a special purpose, 1023 buses and 63 nodes can be designated.

[0083] ~~A space regulated by upper 20 bits of a~~ An address space regulated by the lower 48 bits is divided into a space regulated by the upper 20 bits and a space regulated by the lower 28 bits. The space regulated by the upper 20 bits is divided into an initial register space (Initial Register Space) that is used in a register inherent in a 2048-byte CSR, a register inherent in the IEEE 1394, or the like, a private space (Private Space), and an initial memory space (Initial Memory Space) and the like. ~~A~~ The space regulated by the lower 28 bits, ~~when a space regulated by the upper 20 bits is an initial register space,~~ is divided into a space used as a configuration ROM (Configuration ROM), an initial unit space (Initial Unit Space) used for a purpose inherent in a node, a plug control register (Plug Control Register (PCRs)), or the like.

[0084] FIG. 6 is a diagram ~~for~~ explaining offset addresses, names, and operations of a main CSR. In FIG. 6, A ~~an~~ offset in ~~FIG. 6~~ represents an offset address starting from number

FFFFF0000000h (a number having h at the last ~~end~~ represents a number in hexadecimal notation) at which an initial register space is started. A bandwidth available register (Bandwidth Available Register) having an offset address of 220h represents a band which can be allocated to isochronous communication, and only the value of a node operated as an isochronous resource manager (IRM) is made effective. More specifically, although the CSR in FIG. 5 is included in each node, a bandwidth available register of only the isochronous resource manager is made effective. In other words, the bandwidth available register is substantially included in only the isochronous resource manager. The maximum value is stored in the bandwidth available register when no band is allocated to the isochronous communication, and the value decreases each time a band is allocated to the isochronous communication.

[0085] A channels available register (Channels Available Register) ~~of having an offsets address from~~ 224h to 228h has bits corresponding to channel numbers 0 to 63. A bit of 0 represents that the channel has been allocated. Only the channels available register of a node operating as an isochronous resource manager is effective.

[0086] Returning to FIG. 5, ~~at addresses 200h to 400h in the initial register space,~~ configuration ROMs based on a general ROM format are arranged at addresses 400h to 800h in the initial register space. FIG. 7 is a diagram for explaining the general ROM format. A node serving as a unit of access on the IEEE 1394 bus can have a plurality of units which independently operate while commonly using an address space. Unit directories can indicate the versions and positions of ~~pieces~~ portions of software corresponding to the units. Although the positions of a bus information block (bus info block) and a root directory are fixed, the positions of other blocks are designated by offset addresses.

[0087] FIG. 8 is a diagram showing the details of a bus info block, a root directory, and a unit directory. In Company ID in the bus info block, an identification (ID) number is stored representing a manufacturer of a device ~~is stored~~. In Chip ID, is a unique ID in the world which that is not equal to the IDs of other devices. In addition, according to the standards of IEC 61833, in the unit spec ID of the unit directory of a device which satisfies the IEC 61883 standards, 00h, Aoh, and 2Dh are written in the first octet, the second octet, and the third octet, respectively. Furthermore, 01h is written in the first octet of a unit switch version (unit sw version), and 1 is written in the LSB (Least Significant Bit) of the third octet.

[0088] Since input/output operations of a device are controlled through an interface, a node has a PCR (Plug Control Register) regulated by the IEC 61883 standards at addresses 900h to 9FFh in the initial unit space in FIG. 5. In this case, in order to form a signal path logically similar to an analog interface, ~~the concept of a plug is imaginably~~ virtually constituted ~~created by a register to be embodied~~.

[0089] FIG. 9 is a diagram ~~for~~ explaining the configuration of the PCR. The PCR has an oPCR (output Plug Control Register) representing an output plug and an iPCR (input Plug Control Register) representing an input plug. The PCR also has a register oMPR (output Master Plug Register) and an iMPR (input Master Plug Register) representing an output plug or an input plug inherent in each device. Each device does not have a plurality of oMPRs and a plurality of iPCRs, but each device can have a plurality of oPCRs and a plurality of iPCRs corresponding to each plug depending on the capability of the device. The PCR shown in FIG. 9 has 31 oPCRs and 31 iPCRs. A flow of isochronous data is controlled by operating registers corresponding to these plugs.

[0090] FIGS. 10A to 10D are diagrams showing the configurations of an oMPR, an oPCR, an iMPR, and an iPCR. FIG. 10A shows the configuration of the oMPR, and FIG. 10B shows the configuration of the oPCR. FIG. 10C shows the configuration of the iMPR, and FIG. 10D shows the configuration of the iPCR. In the 2-bit data rate ~~capability~~ capacity position on the Most Significant Bit (MSB) side of the oMPR and the iMPR, a code is stored representing the maximum transmission rate of isochronous data which can be transmitted and received by the device. The broadcast channel base of the oMPR regulates the number of a channel used in a broadcast outputting.

[0091] In the 5-bit number of output plugs position on the LSB side of the oMPR, ~~the number of output plugs included in the device, i.e., the~~ a value is stored representing the number of oPCRs, or output plugs, included in the device ~~is stored~~. In the 5-bit number of input plugs position on the LSB side of the iMPR, ~~the number of input plugs included in the device, i.e., the~~ a value is stored representing the number of iPCRs, or input plugs, included in the device. In the oMPR and the iMPR, Aa non-persistent extension field ~~field~~ and a persistent extension field are regions defined for future expansion ~~in the future~~.

[0092] The on-lines fields of the MSBs of the oPCR and iPCR represent using states of the plugs. More specifically, a value of 1 represents an on-line plug, and a value of 0 represents an off-line plug. The on-line plug represents a state in which transmission can be performed by using the plug. The off-line plug represents a state in which transmission cannot be performed by using the plug. The values of the broadcast connection counter (bcc) of the oPCR and the iPCR are 1 when a broadcast connection is extended. The values are 0 when a broadcast connection is not extended.

[0093] Values of a point-to-point connection counter (pcc) having a 6-bit width of the oPCR and the iPCR represent states of

a point-to-point connection included in the plug. The value of the point-to-point connection counter is any one of values of 1 to 63 when a PtoP connection is extended. The value is 0 when the PtoP connection is not extended. Therefore, a state in which ~~all each of the 7 bits of the broadcast connection counter and the point-to-point connection counter are 0~~ data represents a state in which a connection is not extended to the corresponding plug. ~~and a~~ state in which at least one bit of the 7 bits is 1 data represents a state in which a connection is extended to the plug.

[0094] Values of channel numbers, each having a 6-bit width, of the oPCR and the iPCR represent the numbers of isochronous channels to which the plug is connected. ~~The value of a data rate having a 2-bit width of the oPCR represents a~~ An actual transmission rate of a packet of isochronous data output from the plug is represented by the value of a data rate of the oPCR having a 2-bit width. Three types of transmission rates, ~~e.g. for example~~, 100 Mbps (S100 mode), 200 Mbps (S200 mode), and 400 Mbps (S400 mode) are prepared. The transmission rate represented by the value of the data rate represents a transmission rate which is selected from the three types of transmission rates and by the transmission rate of at which data is transmitted by the connection obtained at that time. The oPCR has Aa code stored in an overhead ID having a 4-bit width ~~of the oPCR that~~ is a value obtained ~~in consideration of~~ from the propagation delay in isochronous communication occurring when stream data is transmitted by isochronous communication. The oPCR also has value of a payload having a value with 10-bit width of the oPCR representing the size of stream data transmitted by the plug in a quadlet unit.

[0095] FIG. 11 is diagram showing the relationship between a plug, a plug control register, and an isochronous channel. The AV devices 71 to 73 are connected to each other through an IEEE

1394 serial bus. The oMPR of AV device 73 regulates the transmission rates of oPCR [0] to oPCR [2]. ~~in which transmission rates and the numbers of oPCR are regulated by the oMPR of the AV device 73, isochronous data having a channel designated by oPCR [1] of AV device 73 designates is transmitted to a channel for transmission of isochronous data to a channel #1 of the IEEE 1394 serial bus.~~ The iMPR of AV device 71 regulates the transmission rates of an iPCR [0] and an iPCR [1]. ~~in which transmission rates and the number of iPCRs are regulated by the iMPR of the AV device 71, The iPCR [0] of AV device 71 designates the input channel #1 of the IEEE 1394 serial bus, is set by the iPCR [0], and the AV device 71 reads the isochronous data transmitted to the channel #1 of the IEEE 1394 serial bus.~~ Similarly, the oPCR [0] of the AV device 72 designates a channel #2 of the IEEE 1394 serial bus, and AV device 72 transmits isochronous data to a channel #2. designated by the oPCR, and ~~The iPRC [1] of AV device 71 designates the channel #2 of the IEEE 1394 serial bus and reads the isochronous data from the channel #2 designated by the iPRC [1].~~

[0096] In this manner, data transmission is performed between devices connected to each other through an IEEE 1394 serial bus.

[0097] ~~However, in the system of this embodiment, by using an AV/C command set is used to regulated as a command for controlling the devices connected to each other through the IEEE 1394 serial bus, control of the devices and decision of the states of the devices can be performed. The AV/C command set will be described below.~~

[0098] When various ~~pieces of information is~~are recorded by the system according to this embodiment, the data structure of a Subunit Identifier Descriptor is to be used and will be described below with reference to FIGS. 12 to 15. FIG. 12 shows the data structure of a Subunit Identifier Descriptor. As shown in FIG. 12, the data structure of a Subunit Identifier Descriptor

~~comprises is constituted by the list of a~~ hierarchical structure ~~of Subunit Identifier Descriptor.~~ When a tuner is used, ~~T~~the list indicates a receivable channel, ~~when a tuner is used,~~ and, when a disk is used, the list indicates the names of songs recorded on the disk. The list of the uppermost layer of the hierarchical structure is called a root list. For example, list 0 is a root corresponding to the lower list of the ~~list of the~~ uppermost layer. Similarly, ~~L~~lists 2 to (n - 1) are similarly root lists.

[0099] The number of root lists is equal to the number of objects.

[0100] Here, when an AV device is a tuner, the object indicates each channel or the like in digital broadcast ~~when an AV device is a tuner.~~ All of the lists of one layer share common information.

[0101] FIG. 13 shows the format of ~~a~~the gGeneral sSubunit iIdentifier dDescriptor. In the General Subunit Identifier Descriptor, the contents describe subsidiary information related to a function ~~is described in contents.~~ The value of a descriptor length field itself is not included. A Generation ID represents the version of an AV/C command set. The present value of the generation ID is "00h" (h represents hexadecimal notation) ~~at the present as shown in FIG. 14.~~ Here, "00h" means that the data structures and command sets are specified in version 3.0 of the AV/C general specification. As shown in FIG. 14, all of the values except for "00h" are preserved and secured for future specifications ~~in the future.~~

[0102] A Size of list ID represents the number of bytes of a list ID. ~~A~~The size of object ID represents the number of an object ID. The Size of object position represents a position (the number of bytes) in a list that is used in ~~referring is~~ performing in control.

[0103] A Number of root object lists represents the number of root object lists. A Root object list id represents an ID for identifying the root object list of the uppermost layer of the independent layers.

[0104] A Subunit dependent length represents the number of bytes of thea subsequent subunit dependent information field. The subunit dependent information ~~is a field~~ representsing information inherent in a function. A Manufacturer dependent length represents the number of bytes of thea subsequent manufacturer dependent information field. The manufacturer dependent information ~~is a field~~ representsing specification information of a vender (maker). When no manufacturer dependent information is ~~not~~ included in a descriptor, the field does not exist.

[0105] FIG. 15 shows an allocation range of the list ID shown in FIG. 13. As shown in FIG. 15, "0000h" to 0FFFh" and "4000h to FFFFh" are secured and preserved as an allocation range for future specifications in the future. "1000h to 3FFFh" and "10000h to max list ID value" ~~are prepared to identify subsidiary information of a function type~~.

[0106] An AV/C command set used in this embodiment will be described below with reference to FIGS. 16 to 21. FIG. 16 shows a stack model of the AV/C command set. As shown in FIG. 16, a physical layer 81, a link layer 82, a transaction layer 83, and a serial bus management 84 conform to the IEEE 1394 standard. An FCP (Function Control Protocol) 85 conforms to the IEC 61883 standard. An AV/C command set 86 conforms to AV/C Digital Interface Command Set General Specification.

[0107] FIG. 17 is a diagram ~~for explaining a command and a response of the FCP (Function Control Protocol) 85 in FIG. 16~~.

[0108] FCP is a protocol for ~~performing the controlling of an AV device on an IEEE 1394 bus~~. As shown in FIG. 17, a controller controls a target, and the target is controlled by the

controller. Transmission of the command or the response of the FCP is performed between nodes by using light transaction of IEEE 1394 asynchronous communication. The target which receives data returns an acknowledge to the controller ~~for~~ confirming reception.

[0109] FIG. 18 is a diagram ~~for more exactly explaining in more detail~~ the relationship between the command and the response of the FCP shown in FIG. 17. A node A and a node B are connected to each other through an IEEE 1394 bus. The node A is a controller, and the node B is a target. ~~For e~~Each of the nodes A and B, have a 512-byte command register and a 512-byte response register ~~are prepared~~. As shown in FIG. 18, the controller writes a command message in a command register 93 of the target to transmit an instruction. In contrast to this, the target writes a response message in a response register 92 of the controller to transmit a response. For the two messages, control information is exchanged. The type of a command set transmitted by the FCP is described in a CTS (ID of the command set) in a data field in FIG. 19 (to be described later).

[0110] FIG. 19 shows the data structure of a packet transmitted in an asynchronous transfer mode of an AV/C command. The AV/C command set is a command set for controlling an AV device, and has a CTS (ID of the command set) = "0000". An AV/C command frame and a response frame are exchanged between nodes using the FCP. In order to reduce a load on the bus and the AV device, a response to the command must be performed within 100 ms. As shown in FIG. 19, the data of an asynchronous packet ~~is constituted by~~ comprises 32 bits (=1 quadlet) in the horizontal direction. The upper half in FIG. 19 shows the header portion of the packet, and the lower half shows a data block. A Destination ID represents a destination.

[0111] The CTS represents the ID of a command set, and is satisfied with CTS = "0000" in the AV/C command set. The field

~~ef-ctype/response~~ field represents a function classification when the packet is a command, and represents a process result of the command when the packet is a response. Commands are roughly classified into four types, ~~i.e. that is~~, (1) a command (CONTROL) for controlling a function from the outside, (2) a command (STATUS) for inquiring about a state from the outside, (3) a command (GENERAL INQUIRY (the presence/absence of support of opcode) and SPECIFIC INQUIRY (the presence/absence of support of opcode and operands), and (4) a command (NOTIFY) for requiring ~~that notification of a change in state is notified to the outside.~~

[0112] A response is returned depending on the type of a command. ~~As r~~Responses to the CONTROL command, may be NOT IMPLEMENTED (not implemented), ACCEPTED (accepted), REJECTED (rejection), and INTERIM (interim) ~~are known.~~ ~~As r~~Responses to the STATUS command, may be NOT IMPLEMENTED, REJECTED, IN TRANSITION (transition is being performed), and STABLE (stability) ~~are known.~~ ~~As r~~Responses to a GENERAL INQUIRY command and SPECIFIC INQUIRY command, may be IMPLEMENTED (implemented) and NOT IMPLEMENTED ~~are known.~~ ~~As r~~Responses to a NOTIFY command, may be NOT IMPLEMENTED, REJECTED, INTERIM, and CHANGED (changed) ~~are known.~~

[0113] A Ssubunit type is set to specify a function in the device.

[0114] For example, a tape recorder/player, a tuner, or the like ~~is~~ may be allocated ~~to as~~ the subunit type. ~~In order to perform a discrimination w~~hen a plurality of subunits of the same type exist, addressing is performed by a subunit id as a discrimination number. Opcode represents a command, and operand represents a parameter of the command. Additional operands are fields and indicates a field added as needed. Padding indicates a field added as needed. Data CRC (Cyclic Redundancy Check) is used for error check in data transmission.

[0115] FIGS. 20A to 20C shows ~~concrete~~ examples of the AV/C command. FIG. 20A shows an concrete example of a ctype/response.

[0116] The upper half in FIG. 20A represents a command, and the lower half in FIG. 20A represents a response. CONTROL is allocated to "0000", STATUS is allocated to "0001", SPECIFIC INQUIRY is allocated to "0010", NOTIFY is allocated to "0011", GENERAL INQUIRY is allocated to "0100". "0101 to 0111" are preserved and secured for future specifications ~~in the future~~. NOT IMPLEMENTED is allocated to "1000", ACCEPTED is allocated to "1001", REJECTED is allocated to "1010", IN TRANSITION is allocated to "1011", IMPLEMENTED/STABLE is allocated to "1100", CHANGED is allocated to "1101", and INTERIM is allocated to "1111". "1110" is preserved and secured for future specifications ~~in the future~~.

[0117] FIG. 20B shows an concrete example of a subunit type. Video Monitor is allocated to "00000", Disk recorder/Player is allocated to "00011", Tape recorder/Player is allocated to "00100", Tuner is allocated to "00101", Video Camera is allocated to "00111", Vender unique is allocated to "11100", Subunit type extended to next byte is allocated to "11110".

[0118] Although a unit is allocated to "11111", ~~— This is used when the device itself is transmitted on, —~~ ~~For example, through an ON/OFF operation of a power supply is known.~~

[0119] FIG. 20C shows an concrete example of an opcode. Tables of an opcode exist for subunit types, respectively. Here, FIG. 20C shows an opcode obtained when the subunit type is a Tape recorder/Player. An Operand is defined for every opcode. In this case, VENDER-DEPENDENT is allocated to "00h", SEARCH MODE is allocated to "50h", TIMECODE is allocated to "51h", ATN is allocated to "52h", OPEN MIC is allocated to "60h", READ MIC is allocated to "61h", WHITE MIC is allocated to "62h", LOAD MEDIUM is allocated to "C1h", RECORD is allocated to "C2h", PLAY is allocated to "C3h", and WIND is allocated to "C4h".

[0120] FIGS. 21A and 21B show ~~concrete~~ examples of an AV/C command and a response. For example, when a reproducing device serving as a target (consumer) is instructed to be ~~reproduced~~play, the controller sends a command shown in FIG. 21A to the target.

[0121] Since this command uses an AV/C command set, CTS = "0000" is satisfied. Since a command (CONTROL) for controlling the device from the outside is used for ctype, ctype = "0000" is satisfied (see FIG. 20A). Since the subunit type is a Tape recorder/Player, subunit type = "00100" is satisfied (see FIG. 20B). An id represents that ID is 0, and id = 000 is satisfied.

[0122] An Opcode ~~is of~~ "C3h" ~~meansing reproduction play~~ (FIG. 20C). An Operand ~~is of~~ "75h" ~~meansing FORWARD~~. When data is reproduced, the target returns a response to the controller as shown in FIG. 21B ~~to the controller~~. In this case, ACCEPTED ~~meansing acceptance~~ is set in the response, and response = "1001" is satisfied (see FIG. 20A). Since FIG. 21B is the same as FIG. 21A except for the response, a separate description thereof will be omitted of the remainder of FIG. 21B is not necessary.

[0123] In this embodiment, ~~Aa control process for controlling the states of devices in this embodiment when in communication with one another and is performed between the devices connected to each other through the IEEE 1394 bus line described above will be described below.~~ As has been described with reference to FIGS. 9 and 10, in this embodiment, a PCR plug regulated by the standards of IEC 61883 ~~and called a PCR~~ is set in a register. When the plug performs isochronous communication ~~is performed by the plug~~, a connection to another device is set. In this case, using the states of use of the plugs are represented by on-line data for the output plug oPCR shown in FIG. 10B and the input plug iPCR shown in FIG. 10D. An on-line state or an off-line state is determined on the basis of the on-line data, so that the device control unit ~~of the device~~ controls the power supplies of

the communication process block and the peripheral circuit thereof.

[0124] A case in which the plug of the device is in an on-line state and a case in which the plug of the device is in an off-line state will be described below with reference to FIG. 22.

[0125] When a connection is or is not extended to the corresponding plug ~~or no connection is extended to the corresponding plug~~, the on-line state and the off-line state exist, respectively. More specifically, when a connection is extended to the corresponding plug to set an on-line state, an active state is set in which an isochronous packet can be output or input ~~is set~~. When a connection is extended to the corresponding plug to set an off-line state, a suspended state is set in which the device is on standby to output or input an isochronous packet ~~is set~~. In addition, when no connection is extended to the corresponding plug to set an on-line state, a ready state is set in which the isochronous packet cannot be output or input ~~is set~~. When no connection is extended to set an off-line state, an idle state is set in which communication cannot be performed ~~is set~~. When data is written in a register ~~constituting of the plug~~, a change is performed between the on-line state and the off-line state, and a change is performed between a state in which a connection is extended and a state in which no connection is extended ~~are performed~~.

[0126] As is apparent from FIG. 22, an isochronous packet is actually input or output in only an on-line state. In this embodiment, ~~in consideration of this point, in the off-line state, a power is not supplied to a circuit for performing isochronous communication.~~ More specifically, the control unit 120 determines the settings of the plugs of the register 107 in the communication processing block 100 shown in FIG. 3 ~~are determined by the control unit 120~~. When it is determined that all of the plugs for the isochronous communication are in off-

line states, a power supply from the power supply circuit 140 to the isochronous block 110 is stopped, so that a power-off state is set. A power is always supplied to the other circuits in the communication processing block 100 while the device ~~in which~~ containing the communication processing block 100 is built operates to set a state in which asynchronous communication can be performed.

[0127] The on-line and off-line states are designed to be set by the power supply mode of the device ~~in which~~ containing the communication processing block 100 is built. For example, as shown in the ~~next~~ {Table 1} below, when the power supply of the device is set in an ON state by operating the power supply key in the operation key pad 150, ~~the states of all of the~~ oPCR and iPCR in the device are set in on-line states. When the device is set in a standby state by operating the power supply key in the operation key pad 150, ~~prepared for the device, the states of all of the~~ oPCR and iPCR in the device are set in off-line states. In the on-line state, an ON state is set for supplying a power to the isochronous communication process unit ~~is set~~. In the off-line state, an OFF state is set for stopping the power supply to the isochronous communication process unit ~~is set~~.

[Table 1]

<u>Mode of Power Supply Mode of Device</u>	<u>Power Supply of Isochronous Communication Process Unit</u>	<u>State of PCR</u>
Standby	OFF	Off-line
ON	ON	On-line

[0128] In addition to directly controlling the power supply with the ease in which the power supply key pad prepared for of the device, is directly operated to control the power supply, a ease in which settings of a the power-on and standby states and a

~~standby state are~~ can be controlled from another device by
~~transmission of the AV/C command from another device.~~

[0129] The flow chart in FIG. 23 shows an example of the process in which the control unit 120 determines the settings of the plugs of register 107 ~~are determined by the control unit 120~~ to perform power supply control of the isochronous block. This process will be described below. In this example, it is assumed, as an initial state, that the power supply of the isochronous block is set in an ON state.

[0130] The control unit 120 checks whether the states of the plugs in the register 107 are changed from the on-line states to the off-line states ~~or not~~ (step S11). If the states are not changed, the control unit 120 is on standby ~~in this state~~. If ~~the~~ a change from the on-line states to the off-line states is detected, a power-off state is set stopping the power supply from the power supply circuit 140 to the isochronous block 110 ~~is stopped to set a power-off state~~ (step S12).

[0131] After the power-off state is set, ~~it is checked whether~~ the states of the plugs in the register 107 are checked to determine whether there is a ~~changed~~ from the off-line states to the on-line states ~~or not~~ (step S13). If the states are not changed, the control unit 120 is on standby. If ~~the~~ a change from the off-line states to the on-line states is detected, a power-on state is set starting the power supply from the power supply circuit 140 to the isochronous block 110 ~~is started to set a power-on state~~ (step S14). Thereafter, the flow returns to the decision in step S11.

[0132] In this manner, on the basis of the settings of the on-line and off-line states ~~and the off-line states~~ of the plugs for isochronous communication, the power supply is controlled ~~as a part~~ for performing signal processing for ~~the~~ isochronous communication ~~is controlled~~. For this reason, during ~~in~~ a period of time in which isochronous communication need not be performed,

the power supply of ~~the part~~ for performing a ~~process~~ for isochronous communication can be turned off, so that a power consumption of the communication circuit ~~can be~~ is reduced. In this case, since power is always supplied to the ~~part~~ portion of the communication circuit for performing signal processing for ~~the isochronous communication to set the portion in an operation state~~, the device can always asynchronously communicate with another device. On the network configuration, the corresponding device (node) ~~keeps~~ remains connected to the bus line. ~~7~~ b Bus reset or the like does not occur, ~~re-adding of a node ID~~ caused by the bus reset is not performed, and a controller on the network need not frequently perform the bus reset. For this reason, athe control process of the network is simplified.

[0133] When the power supply of athe signal processing unit for isochronous communication is turned off, the device can asynchronously communicate with another device. For this reason, an instruction is transmitted to ~~for turning on~~ the power supply of athe signal processing unit of the device for isochronous communication ~~of the device is transmitted~~ such that the AV/C command, and the corresponding process, or the like from another device by ~~the asynchronous communication, and the corresponding process~~ can also be performed. Even though the power supply of the isochronous block is in an OFF state, a measure there is power to transmit stream data from another device ~~can be made~~.

[0134] In the process shown in FIG. 23, on the basis of detection of the on-line and off-line states ~~and the off-line states~~ of the plugs, the power supply of the isochronous block is controlled independently of another block. However, on the basis of detection of other states, the power supply of the isochronous block may be ~~performed~~ performed independently of another block. The flow chart in FIG. 24 shows another example. In this example, in the output plug oPCR shown in FIG. 10B and the input plug iPCR shown in FIG. 10D, the ~~setting~~ states of the connections are decided on

the basis of a value of a broadcast connection counter (bcc) and the value of a point-to-point connection counter (pcc).

[0135] When it is decided ~~by the decision that any connection does not set,~~ the state of all bcc or pcc are changed, the power supply is turned off.

[0136] More specifically, as shown in FIG. 24, if the power supply of the isochronous block is initially in an ON state, ~~as an initial state,~~ the control unit 120 ~~decides~~ detects the states of the plugs in the register 107 ~~and~~ decides whether the values of the bcc and the pcc of all of the plugs are changed to 0 data or not (step S21). When the values are not changed to 0, the control unit 120 is on standby.

[0137] When it is detected that the values of the bcc and the pcc of all of the plugs are 0-data, the power supply from the power supply circuit 140 to the isochronous block 110 is stopped to set a power-off state (step S22).

[0138] After the power-off state is set, the states of the plugs in the register 107 are ~~decided~~ detected, and it is decided whether any one of the bits of the ~~value of the bcc or the pcc of any one of the plugs is~~ changed to 1 data or not (step S23). When the value is not changed, the control unit 120 is on standby. When it is detected that any one of the bits of the ~~value of the bcc or the pcc of any one of the plugs is~~ 1-data, the power supply from the power supply circuit 140 to the isochronous block 110 is started to set a power-off on state (step S24). Thereafter, the flow returns to the decision in step S21.

[0139] When the process is performed as described above, ~~as in~~ in the case of the flow chart in FIG. 23, the presence/absence of isochronous communication is reliably decided to control the ON or OFF state of the power supply of the isochronous block. When the isochronous communication need not be performed, the power supply of the block for performing the communication process is

turned off, so that ~~at~~ the power consumption of the communication circuit ~~can be~~ is reduced.

[0140] In the flow charts in FIGS. 23 and 24, the state is decided of the plugs for isochronous communication ~~are decided~~. When the isochronous communication need not be performed, the power supply is turned off for ~~of the block for the isochronous communication process is turned off~~. However, the power supply of the block for the isochronous communication process can be independently controlled depending on the operation state of the power supply key of the device. More specifically, when a power-on state is set as ~~a power-on state off~~ for the device (~~i.e., that is,~~ the device is set in an operation state), both ~~of the power supply of the block for an isochronous communication process block and the power supply of the block for an asynchronous communication process block~~ are turned on to set in a standby state (i.e., that is, only the control unit of the device is set in an operation state)~~),~~. ~~The power supply of the block for the isochronous communication process block may be turned off, and only the power supply of the block for the asynchronous communication process block may be kept in an ON state.~~ In this case, a power-off state can be set independently of a standby state, so as ~~to a mode in which that~~ both the power supplies, ~~i.e., that is,~~ the power supply ~~of the block for the isochronous communication process block and the power supply of the block for the asynchronous communication process block~~ can be turned off ~~may be able to be set~~.

[0141] In the embodiment described above, power supply control is performed only in ~~only the~~ block for directly performing a communication process. However, power supply control for a circuit block ~~dependent~~ ing on the format of stream data for performing a transmission or a reception process ~~or a reception process~~ in the block also ~~may also be~~ performed while being

linked with the power supply control ~~of the block for performing~~ the isochronous block.

[0142] For example, when the power supply is turned off for ~~of~~ the isochronous communication block in the disk recording/reproducing device 50, ~~is turned off,~~ the power supplies may be turned off ~~of the block for~~ the block performing a data recording process of data obtained in this block in the ATRAC system and ~~the block for~~ the block performing a data reproducing process ~~the data in the ATRAC system to transmit the data to the isochronous communication block~~ ~~may be turned off.~~

[0143] In addition, for example, when the power supply in the IRD 10 for ~~of the isochronous communication block in the IRD 10~~ is in an OFF state, the portion of the block for that performing a process in which video data of the MPEG system is received ~~by the device in the block~~ is in a power-off state, so that a receiving process may not be performed for receiving ~~of~~ the video data or the like ~~which that is stream data output from the isochronous communication block may not be performed.~~ In this manner, a ~~power consumption of the device can be~~ is further reduced.

[0144] In the embodiment described above, the power supply of the isochronous communication block is controlled on the basis of the state of a register in the communication process block, ~~the power supply of the isochronous communication block is~~ ~~controlled.~~ However, the power supply of the isochronous communication block may be automatically controlled ~~while being~~ when the power supply is linked with ~~to any state of the device.~~ For example, in a device using a recording medium such as the disk recording/reproducing device 50, the power supply of the isochronous communication block may be controlled ~~while being~~ when the power supply is linked with ~~to the loading of a recording medium (disk) on~~ in the device. More specifically, when there is no recording medium is loaded on in the device, ~~it is~~

~~decided that stream data need~~ does not need to be input to or output by the device, and the control unit sets the power supply of the isochronous communication block into an off state. When the recording medium is loaded, data can be recorded or reproduced by the device.

[0145] For this reason, the control unit may set the power supply of the isochronous communication block in an ON state. In this manner, on the basis of the state of the device, the power supply of the isochronous communication block can be appropriately controlled. The disk recording/reproducing device 50 of this embodiment is a recording device for audio data.

[0146] ~~However~~ Similarly, when a recording/reproducing device is used for recording video data or the like on a medium (disk, tape, memory card, or the like) and reproducing the video data, ~~is used, similarly,~~ the power supply of the isochronous communication process unit may be controlled ~~while being~~ when the power supply is linked with to the presence/absence of a loaded medium.

[0147] In the embodiment described above, ~~as having a device in which containing~~ the communication processing block 100 shown in FIG. 3 ~~is built~~, the IRD 10 and the disk recording/reproducing device 50 are described. However, the present invention also can also be applied to a case in which in an embodiment having a similar communication process block is built in another device and connected to a the bus line to perform synchronous and asynchronous communication and asynchronous communication.

[0148] In the embodiment described above, the power supply to the block that for performing an isochronous communication process is controlled independently ~~of a from the block for that performing~~ another communication process. However, the power supply of the block ~~(i.e., a block for asynchronous communication)~~ for that performing the asynchronous communication process may be controlled independently of the

block ~~for that~~ performing the other communication process. More specifically, for example, the power supply of the asynchronous signal processing unit 106 and the power supply of the asynchronous data buffer 105 in the communication processing block 100 shown in FIG. 3 are designed to be controlled independently of the other circuits in the communication processing block 100. When the control unit 120 decides that ~~only asynchronous communication need not be performed~~, the power supply is stopped to the asynchronous signal processing unit 106 and the asynchronous data buffer 105 ~~are stopped~~.

[0149] In the state ~~in during~~ which ~~only the asynchronous communication does not need not to be performed~~, a monitoring video camera is used as a device having at the communication process block 100, ~~built therein, and photographing is~~ continuously executed by the monitoring video camera is in a constant state that continuously executes video data. A the process in which video data obtained by the photographing is always of continuously transmitting video data to a recording device or a monitor is performed in an isochronous communication mode. It is assumed that a command for ~~performing operation controlling of the video camera does need not need to be~~ transmitted ~~by during the asynchronous communication~~.

[0150] In such a case, when the power supply is off for the block ~~for that processes~~ asynchronous communication, is turned off, a the isochronous communication process can be is performed with using a small power consumption, and monitoring can be continuously performed in a constant state. Even though a device is used, except for the monitoring camera is used, when there must be continuous transmission of serial stream data must be ~~continuously transmitted in a constant state, similarly, only the~~ block for processing the asynchronous communication may be independently controlled.

[0151] In the embodiment described above, a network ~~constituted by comprising~~ an IEEE 1394 bus has been described. However, the present invention can also be applied ~~to a case in~~ an embodiment in which the same data transmission is performed between devices connected through another network configuration (~~e.g. for example~~, USB). ~~As a~~ In addition to the bus line described above, the transmission path between the devices, may be a wireless transmission path may also be used in addition to the bus line described above. ~~As~~ With the wireless transmission path, when a network is ~~constituted between~~ comprises a plurality of devices connected by a wireless communication ~~of the standards~~ called, ~~e.g. for example~~, Bluetooth, the power supply of at least one of ~~at the~~ blocks for performing a synchronous or an asynchronous communication process ~~and a block for performing an asynchronous communication process~~ can be independently controlled by the devices in the network.

[0152] According to a control method described in ~~the~~ a first aspect of the present invention, ~~at the~~ the power supply is independently controlled of only a part for the portion of the circuit that executesing at the communication process in at the synchronous communication mode is independently controlled. For example, when synchronous communication ~~does need~~ does not need to be performed, the power supply ~~of the for that~~ for that portion can be turned off. Therefore, power may be supplied to the portion that part for executesing the communication process in the synchronous mode only when synchronous communication must be performed, so that the power required for the communication process can be is reduced.

[0153] According to a control method described in ~~the~~ a second aspect of the present invention, in the ~~embodiment invention~~ described in the first aspect, the power supply is turned off of the part for the portion of the circuit that executesing the communication process in the synchronous communication mode is

~~turned off in a~~ during the period in which the ~~communication~~ is not executed in the synchronous communication mode, ~~is not executed,~~ and a ~~state in which only a~~ during which the power supply of a part is turned on for the portion of the circuit that ~~for executing~~ at the communication process in an asynchronous communication mode ~~is turned on is set.~~ For this reason, the power supply of ~~only the~~ communication process unit in the asynchronous communication mode ~~may be~~ is turned on in a period ~~in which the~~ when communication in the synchronous communication mode is not performed, and the power required for the communication process ~~can be~~ is reduced.

[0154] According to a control method according to ~~the~~ a third aspect of the present invention, in the ~~invention~~ embodiment described in the second aspect, ~~at the~~ power supply also is turned off for the portion of the circuit that ~~of a part for performing~~ a process dependent on at the format of data communicated in the synchronous communication mode ~~is also turned off,~~ so that a power consumption ~~can be~~ is reduced.

[0155] According to a control method according to ~~the~~ a fourth aspect of the present invention, in the ~~invention~~ embodiment described in the first aspect, ~~a connected network is a~~ the network uses a bus line to connect devices in which communication in ~~an~~ the asynchronous communication mode and communication in ~~at the~~ synchronous communication mode ~~are connected to each other by a bus line which can coexist on the same line using in a time divisional manner on the same line.~~ For this reason, the power required is effectively reduced for communication between the devices when communication is executed ~~by using the network constituted such that connections is performed by the bus line having the above configuration can be effectively reduced.~~

[0156] According to the control method described in ~~the~~ a fifth aspect of the present invention, in the ~~invention~~ embodiment described in the fourth aspect, when ~~at the~~ setting of a plug for

~~at~~he synchronous communication mode is in an OFF state, ~~at~~he power supply is turned off for the portion of the circuit that ~~of a part for executing~~ athe communication process in the synchronous communication mode ~~is turned off~~. For this reason, the power supply can be preferably controlled for the portion of the circuit that ~~of the part for executing~~ the communication process in the synchronous communication mode ~~can be preferably controlled~~.

[0157] According to ~~the~~a seventh aspect of the present invention, in the ~~invention-embodiment~~ described in the fourth aspect, when a connection is not set for synchronous communication with another device in ~~at~~he network ~~is not set~~, ~~at~~he power supply is turned off for the portion of the circuit that ~~of a part for executing~~ athe communication process in a synchronous communication mode ~~is turned off~~. For this reason, the power supply can be preferably controlled for the portion of the circuit that ~~of a part for executing~~ the communication process in the synchronous communication mode ~~can be preferably controlled~~.

[0158] According to a control method described in ~~the~~a ninth aspect of the present invention, in the ~~invention-embodiment~~ described in the first aspect, when ~~unloading a~~ the recording medium ~~is~~ is not loaded~~detected~~, the power supply is turned off ~~of the part for the portion of the circuit that~~ executing the communication process in the synchronous communication mode, ~~is turned off~~, and, when the recording medium is loaded, the power supply is turned on ~~of the part for the portion of the circuit that~~ executing the communication process in the synchronous communication mode ~~is turned on~~.

[0159] For this reason, the power supply of the communication process unit in the synchronous communication mode is ON/OFF-controlled ~~while being~~ when the power supply is linked with ~~to the loading/unloading of~~ the recording medium. For example, when

data that is read from the recording medium is transmitted to the network in the synchronous communication mode, or when data that is received in the synchronous communication mode through the network is recorded on the recording medium, if these processes cannot be executed, athe power supply is automatically turned off for the ~~ef a~~ communication process unit in the synchronous communication mode, is automatically turned off, and the power supply can be preferably controlled for ~~ef the~~ communication process unit in the synchronous communication mode ~~ean be preferably controlled in~~ accordance with athe state of athe device.

[0160] According to a control method described in thean eleventh aspect of the present invention, athe power supply is independently controlled for the portion of the circuit that ~~supply ef only a part for executesing~~ a communication process in an asynchronous communication mode ~~is independently controlled,~~ and, for example, when asynchronous communication does not need ~~not to~~ be performed, the power supply for that portion of the ~~part can~~ be turned off. Therefore, power may be supplied to the ~~part for portion that~~ executesing the communication process in the asynchronous communication mode only when the asynchronous communication must be performed, so that the power required for the communication process ~~ean be~~ is reduced.

[0161] According to a control method described in thea twelfth aspect of the present invention, in the ~~invention embodiment~~ described in the eleventh aspect, communication is continuously executed in the synchronous communication mode ~~is continuously executed,~~ and, when communication in the asynchronous communication mode does not need ~~not to~~ be performed, the power supply ~~ef the part for~~ is turned off for the portion of the circuit that ~~executesing~~ the communication process in the asynchronous communication mode ~~is turned off.~~ For example, as in transmission or the like in the asynchronous communication

mode of video data from a monitoring camera, in a synchronous communication mode, continuous data communication is performed in a constant state, and, when control data or the like related to the data communication in the asynchronous communication mode does not need not to be performed, a ~~process for~~ communication process can be performed with a small power consumption.

[0162] According to a communication device described in ~~the~~ a thirteenth aspect of the present invention, ~~only a the~~ power supply of a first communication process unit ~~for that~~ executing a communication process in a synchronous communication mode can be independently controlled, ~~and,~~ for example, when synchronous communication does not need not to be performed, ~~the~~ power supply can be turned off for ~~of only the first communication process unit can be turned off.~~ For this reason, in accordance with a communication state decided by a control unit, ~~the~~ power can be turned off for ~~consumption of the first communication process unit can be turned off~~ to reduce a power consumption.

[0163] According to a communication device described in ~~the~~ a fourteenth aspect of the present invention, in the ~~invention~~ embodiment described in the thirteenth aspect, ~~by control of the control unit, in~~ during a period in which communication is not executed in the synchronous communication mode, ~~is not executed,~~ the control unit turns off the power supply of the first communication process unit, is turned off, and the power supplies are set in ON states for ~~of a second communication process unit and an input/output unit are set in ON states.~~ For this reason, ~~only the second communication process unit may be~~ is powered on ~~in~~ during the period in which the communication in the synchronous communication mode is not performed, and the power required for the communication process can be is reduced.

[0164] According to a communication device described in ~~the~~ a fifteenth aspect of the present invention, in the ~~invention~~

embodiment described in the fourteenth aspect, a data processing unit ~~for performing~~ a process dependent on a format of data communicated in the synchronous communication mode, ~~is comprised,~~ and, ~~by the control of~~ and the control unit, turns off the a power supply of the data processing unit ~~is turned off in~~ during the period in which ~~the~~ communication in the synchronous communication mode is not executed. For this reason, a power consumption ~~can be~~ is reduced.

[0165] According to a communication device described in ~~the~~ a sixteenth aspect of the present invention, in the invention embodiment described in the thirteenth aspect, ~~a network~~ connected to the an input/output unit is connected to a network by a bus line. in which communication on the same line in such a network in an asynchronous or synchronous communication mode ~~and communication in a synchronous communication mode are~~ constituted by a bus line which can coexist in a using time divisional manner ~~on the same line~~.

[0166] For this reason, the power required is effectively reduced for communication between communication devices ~~for in~~ the network ~~constituted such that where the connections is to the~~ network are performed by the bus line having the above configuration ~~can be effectively reduced~~.

[0167] According to a communication device described in ~~the~~ a eighteenth aspect of the present invention, in the invention embodiment described in the sixteenth aspect, when ~~at~~ the control unit decides that a plug for the synchronous communication mode is set in an OFF state, the control unit turns off the power supply of the first communication unit. For this reason, ~~control of the power supply can be preferably controlled for of the first~~ communication unit ~~for that~~ executing the communication process in the synchronous communication mode ~~can be preferably performed~~.

[0168] According to a communication device described in ~~thea~~ twentieth aspect of the present invention, in the ~~invention~~ embodiment described in the sixteenth aspect, when ~~a~~the control unit decides that a connection is not set for synchronous communication with another device in ~~a~~the network ~~is not set~~, the control unit turns off the power supply of the first communication unit. For this reason, ~~control of the~~ power supply can be preferably controlled for ~~of the~~ first communication unit ~~for that executes~~ the communication process in the synchronous communication mode ~~can be preferably performed~~.

[0169] According to a communication device described in ~~thea~~ twenty-first aspect of the present invention, in the ~~invention~~ embodiment described in the thirteenth aspect, when the control unit detects removal of the recording medium from a loading unit, ~~on which a recording medium is loaded is comprised,~~ the control unit turns off the power supply of the first communication process unit. ~~when the control unit detects unloading the recording medium on the loading unit, and t~~The control unit turns on the power supply of the first communication process unit when the control unit detects loading of the recording medium on in the loading unit. For this reason, the power supply of the first communication process unit is automatically ON/OFF-controlled when the power supply is while being linked with to loading/unloading of the recording medium. For example, when data that is read from the recording medium is transmitted to the network in the synchronous communication mode, or when data that is received in the synchronous communication mode through the network is recorded on the recording medium, if these processes cannot be executed, the power supply is automatically turned off for ~~of the~~ communication process unit in the synchronous communication mode ~~is automatically turned off~~.

[0170] Therefore, the power supply ~~of~~ for the communication process unit in the synchronous communication unit ~~can be~~ is preferably controlled in accordance with a state of ~~at~~ the device.

[0171] According to a control device described in ~~the~~ a twenty-second aspect of the present invention, ~~by controlling a control unit,~~ is used to independently control ~~only~~ a power supply of a second communication process unit for executing a communication process in an asynchronous communication mode ~~can be independently controlled~~. For example, when ~~the~~ asynchronous communication does not need ~~not to be performed,~~ only the power supply of the second communication process unit can be turned off. Therefore, in accordance with the state of communication determined by the control unit, the power supply of the second communication unit can be turned off to reduce a power consumption ~~in accordance with a state of communication decided by the control unit~~.

[0172] According to a communication device described in ~~the~~ a twenty-third aspect of the present invention, in the ~~invention~~ embodiment described in the twenty-second aspect, communication in the synchronous communication mode is continuously executed by the first communication process unit, and, when the second communication process unit does not need to perform communication in an asynchronous communication mode, ~~need not be performed in the second communication process unit,~~ the control unit turns off the power supply of the second communication process unit. For this reason, for example, as in transmission or the like of video data from a monitoring camera in the synchronous communication mode, continuous data communication is performed in a constant state, and, ~~e~~ Control data or the like related to the data communication does not need ~~not to be~~ transmitted in the asynchronous communication mode, and ~~the process for~~ communication process can be performed with a ~~small~~ less power consumption.

[0173] Having described preferred embodiments of the invention with reference to the accompanying drawings, it is to be understood that the invention is not limited to those precise embodiments and that various changes and modifications could be effected therein by one skilled in the art without departing from the spirit or scope of the invention as defined in the appended claims.

MARKED-UP COPY OF AMENDED CLAIMS

What is claimed is:

1. (AMENDED) A ~~control~~ method for controlling power supplies of a device connected to a predetermined network, and said device having a first communication process unit for executing communication in an asynchronous communication mode and having a second communication process unit for executing communication in a synchronous communication mode, the method comprising:

~~the power supply control step of controlling a first power supply of the second communication process unit for executing a communication process in the synchronous communication mode; and~~

independently controlling of a second power supply of the first communication process unit for executing a communication process in the asynchronous communication mode, said first power supply being controlled independently of said second power supply.

2. (AMENDED) The control method according to claim 1, wherein, ~~in the power supply control step the said first power supply of the second communication process unit for executing the communication process in the synchronous communication mode is turned off in during a period in which the communication in the synchronous communication mode is not executed, and only a said second power supply of the first communication process unit for executing the communication process in the asynchronous communication mode is turned on is set in an ON state during said period.~~

3. (AMENDED) The control method according to claim 2, wherein, ~~in the power supply control step a said first power supply of a part for performing a process depending on a format of data communicated in the synchronous communication mode is~~

turned off when a process is performed dependent on a format of data communicated in the synchronous communication mode.

4. (AMENDED) The control method according to claim 1, wherein the predetermined network ~~is constituted by~~ includes a bus line on which first communication data in the asynchronous communication mode and second communication data in the synchronous communication mode are transmitted, ~~such that both the and said first and second communication data can coexist in a~~ on said bus line using time divisional manner on the same line.

5. (AMENDED) The control method according to claim 4, wherein, ~~in the power supply control step said first power supply is controlled on the basis of a setting of a plug for the synchronous communication mode, the power supply of the second communication process unit for executing the communication process in the synchronous communication mode.~~

6. (AMENDED) The control method according to claim 5, wherein ~~in the power supply control step said first power supply is turned off when the said setting of the said plug for the synchronous communication mode is in an OFF off state, the power supply of the part for executing the communication process in the synchronous communication mode is turned off.~~

7. (AMENDED) The control method according to claim 4, wherein, ~~in the power supply control step said first power supply is controlled on the basis of a setting state of a connection with another device in said network for synchronous communication with another device in a network, a power supply of a communication process unit for executing the communication process in the synchronous communication mode is controlled.~~

8. (AMENDED) The control method according to claim 7, wherein, ~~in the power supply control step said first power supply is turned off, when a said connection for synchronous communication with said another device is not made with another device in a network is not set, the power supply of the part for~~

~~executing the communication process in the synchronous communication mode is turned off.~~

9. (AMENDED) The control method according to claim 1, wherein the said device has a loading means unit operable to load for loading a recording medium, and, in the power supply control step, a said first power supply of a second communication control unit for executing the communication process in the synchronous communication mode is controlled on the basis of a loading state of the said recording medium on the in said loading means unit.

10. (AMENDED) The control method according to claim 9, wherein, ~~in the power supply control step the said first power supply of the second communication process unit for executing the communication process in the synchronous communication mode is turned off when unloading the said recording medium is detected~~removed from said loading unit; and

~~the said first power supply of the second communication process unit for executing the communication process in the synchronous communication mode is turned on when the said recording medium is loaded in said loading unit.~~

11. (AMENDED) A ~~control method for controlling power supplies of a device connected to a predetermined network, and said device having a first communication process unit for executing communication in a synchronous communication mode and having a second communication process unit for executing communication in an asynchronous communication mode, the method comprising:~~

~~the power supply control step of controlling a first power supply of the second communication process unit for executing a communication process in the asynchronous communication mode; and~~

~~independently of controlling a second power supply of the first communication process unit for executing a communication process in the synchronous communication mode, said~~

first power supply being controlled independently of said second power supply.

12. (AMENDED) The control method according to claim 11, wherein, ~~in the power supply control step,~~ communication in the synchronous communication mode is continuously executed, and, said first power supply is turned off when communication in the asynchronous communication mode need is not be performed, ~~the power supply of the second communication process unit for executing the communication process in the asynchronous communication mode is turned off.~~

13. (AMENDED) A communication device which is connected to a predetermined network, ~~and which can~~ said device performing synchronous communication in a synchronous communication mode through the network and asynchronous communication in ~~thean~~ asynchronous communication mode through the network, said device comprising:

a first communication process unit for performing a first communication process in ~~the~~ said synchronous communication mode;

a second communication process unit for performing a second communication process in ~~thesaid~~ asynchronous communication mode;

an input ~~/and~~ output unit for performing inputting ~~/and~~ outputting between ~~thesaid~~ first and said second communication process units and the network; and

a control unit for controlling ~~thesaid~~ synchronous communication and ~~thesaid~~ asynchronous communication ~~teby~~ independently controlling ~~only the a~~ power supply of ~~thesaid~~ first communication process unit.

14. (AMENDED) The communication device according to claim 13, wherein ~~thesaid~~ control unit turns off ~~thesaid~~ power supply ~~of the first communication process unit in during~~ a period in which communication is not executed in the said synchronous

communication mode, ~~is not executed and said control unit to sets~~
~~the a~~ power supply of ~~the said~~ second communication process unit
in an ~~ON~~ on state during said period.

15. (AMENDED) The communication device according to
claim 14, further comprising:

a data processing unit for performing a process
~~dependent~~ing on a format of data communicated in ~~the said~~
synchronous communication mode; and

~~wherein the said control unit turns off a power~~
supply of ~~the said~~ data processing unit ~~in during said the period~~
in which ~~the communication is not executed in the said~~
synchronous communication mode ~~is not executed~~.

16. (AMENDED) The communication device according to
claim 13, wherein, on the network, ~~communication data in the said~~
asynchronous communication mode transmits asynchronous
communication data and communication data in the said synchronous
communication mode transmits synchronous communication data, and
using time division, said asynchronous communication data and
said synchronous communication data are transmitted such that
~~both the communication data can coexist in a time divisional~~
~~manner on the a common bus same line.~~

17. (AMENDED) The communication device according to
claim 16, wherein ~~the said~~ control unit turns off ~~the said~~ power
supply of ~~the said~~ first communication control unit on the basis
of a setting of a plug for ~~the said~~ synchronous communication
mode.

18. (AMENDED) The communication device according to
claim 17, wherein ~~the said~~ control unit turns off ~~the said~~ power
supply of ~~the said~~ first communication process unit when ~~the said~~
control unit determines that ~~the a~~ setting of ~~the said~~ plug for
~~the said~~ synchronous communication mode is in an ~~OFF~~ off state.


19. (AMENDED) The communication device according to
claim 16, wherein ~~the said~~ control unit turns off ~~the said~~ power

Application No. 09/870,047

If there are any additional charges in connection with this requested amendment, the Examiner is authorized to charge applicant's Deposit Account No. 12-1095 therefor.

Respectfully submitted,

LERNER, DAVID, LITTENBERG,
KRUMHOLZ & MENTLIK, LLP

A handwritten signature in black ink, appearing to read "Robert B. Cohen", written over the printed name.

ROBERT B. COHEN
Reg. No. 32,768

600 South Avenue West
Westfield, NJ 07090-1497
Telephone: (908) 654-5000
Facsimile: (908) 654-7866

supply of ~~thesaid~~ first communication process unit on the basis of a ~~setting state~~ of a connection with another device in the network for synchronous communication ~~with another device in the network~~.

20. (AMENDED) The communication device according to claim 19, wherein ~~thesaid~~ control unit turns off ~~thesaid~~ power supply of ~~thesaid~~ first communication control unit when ~~thesaid~~ control unit determines that ~~thesaid~~ connection ~~for the synchronous communication with said another device in the network~~ is not ~~set~~made.

21. (AMENDED) The communication device according to claim 13, further comprising:

a loading unit for loading a recording medium; and
a loading detection unit for detecting a loaded condition in which a recording medium is loaded in said loading unit and an unloaded condition in which said loading/unloading a recording medium on the is not loaded in said loading unit, and wherein when thesaid loading detection unit detects said unloaded condition, unloading the recording medium on the loading unit, thesaid control unit turns off thesaid power supply of thesaid first communication process unit, and when thesaid loading detection unit detects said loaded condition, loading the recording medium on the loading unit, thesaid control unit turns on thesaid power supply of said first communication process unit.

22. (AMENDED) A communication device which is connected to a predetermined network, and which can said device performing synchronous communication in a synchronous communication mode through the network and asynchronous communication in thean asynchronous communication mode through the network, said device comprising:

a first communication process unit for performing a first communication process in ~~thesaid~~ synchronous communication mode;

a second communication process unit for performing a second communication process in ~~thesaid~~ asynchronous communication mode;

an input ~~/and~~ output unit for performing inputting ~~/and~~ outputting between ~~thesaid~~ first and said second communication process units and the network; and

a control unit for controlling ~~thesaid~~ synchronous communication and ~~thesaid~~ asynchronous communication ~~so that only~~ by independently controlling a ~~the~~ power supply of ~~thesaid~~ second communication process unit ~~can be independently controlled~~.

23. (AMENDED) The communication device according to claim 22, wherein, communication in the synchronous communication mode is continuously executed by ~~thesaid~~ first communication process unit, and, said control unit turns off said power supply of said second communication process unit when communication in ~~thesaid~~ asynchronous communication mode does not need not to be performed by ~~thesaid~~ second communication process unit, ~~the control unit turns off the power supply of the second communication process unit.~~